

# Four beam light band



**Please read manual carefully before use.**



19	macro	0-49	No function
		50-149	Auto
		150-229	sound
		230-240	reset

## Display menu:

DMX address	1-512
Channel mode	19CH
Show mode	DMX Auto sound
Sound Sense	0-100
Pan inversion	-Yes.-No.
Tilt 1 inversion	-Yes.-No.
Tilt 2 inversion	-Yes.-No.
Tilt 3 Reverse	-Yes.-No.
Tilt 4 inversion	-Yes.-No.
Back Light	On / off
Firmware-version	A 1.0 AB1.0
Defaults	-Yes.-No.
reset	-Yes.-No.

19CH	function	DMX value	describe
1	x-axis	0-255	0~540°
2	X infinity	0-49	NO FUNCTION
		50-151	Inverse clock infinitely rotating (from fast to slow)
		152-255	Clockwise endless rotation (from slow to fast)
3	Y-axis 1	0-255	0~110°
4	Y-axis 2	0-255	0~110°
5	Y-axis 3	0-255	0~110°
6	Y-axis 4	0-255	0~110°
7	Total dimming	0-255	From dark to bright
8	stroboflash	0	NO FUNCTION
		1-255	Stroboscopic speed from slow to fast (1HZ~25HZ)
9	Beam 1	0-23	NONE
		24-47	RED
		48-71	GREEN
		72-95	BLUE
		96-119	WHITE
		120-143	Red +green
		144-167	Red+ blue
		168-191	Green+ blue
		192-215	Red+green+blue.
		216-255	Red + green + blue + white
10	Beam 2	0-23	NONE
		24-47	RED
		48-71	GREEN
		72-95	BLUE
		96-119	WHITE

		120-143	Red +green
		144-167	Red+ blue
		168-191	Green+ blue
		192-215	Red+green+blue.
		216-255	Red + green + blue + white
11	Beam 3	0-23	NONE
		24-47	RED
		48-71	GREEN
		72-95	BLUE
		96-119	Red +green
		120-143	Red+ blue
		144-167	Green+ blue
		168-191	Red+green+blue.
		216-255	Red + green + blue + white
		12	Beam 4
24-47	RED		
48-71	GREEN		
72-95	BLUE		
96-119	Red +green		
120-143	Red+ blue		
144-167	Green+ blue		
168-191	Red+green+blue.		
192-215	Red + green + blue + white		
216-255	NONE		
13	Light belt dimming	0-255	
14	stroboflash	0	NO FUNCTION
		1-255	Stroboscopic speed from slow to fast (1HZ~25HZ)
15	5050Lamp belt 1	0-24	NO FUNCTION
		25-49	RED
		50-74	GREEN

		75-99	blue
	5050Lamp belt 1	100-124	Red +green
		125-149	Red+ blue
		150-174	Green +blue
		175-255	Red+green, +blue.
16	5050Lamp belt 2	0-24	No function
		25-49	Red
		50-74	green
		75-99	blue
		100-124	Red +green
		125-149	Red+ blue
		150-174	Green +blue
		175-255	Red+green, +blue.
17	5050Lamp belt 3	0-24	No function
		25-49	Red
		50-74	green
		75-99	blue
		100-124	Red +green
		125-149	Red+ blue
		150-174	Green +blue
		175-255	Red+green, +blue.
18	5050Lamp belt 4	0-24	No function
		25-49	Red
		50-74	green
		75-99	blue
		100-124	Red +green
		125-149	Red+ blue
		150-174	Green +blue
		175-255	Red+green, +blue.