

SHOW

Addr	A001-A512	512 DMX
CHnd	21CH	21CH
	15CH	15CH
SLnd	MAST	AUTO
	Soun	SOUND
	SL 1	DMX
	SL 2	Slave
SHnd	SH 0	Effect 0
	SH 1	Effect 1
	SH 2	Effect 2
	SH 3	Effect 3
SEnS	0-99	sound -speed
bLAnd	bLAc	No DMX-0
	Auto	No DMX-Sound
	Soun	No DMX-Auto
	HoLd	No DMX-Auto1
LEd	OFF	Show-Off
	ON	Show-On
dISP	no	Show-P
	YES	Show-R
rPAN	no	X-motor-P
	YES	X-motor-R
rTiL	no	Y-motor-P
	YES	Y-motor-R
REST	YES	REST

15CH

Channel	Functions	DMX values
1	X	0-255
2	Y	0-255
3	X-Y Speed	0-255
4	Y-360	6-255
5	Dimming	0-255

6	Strobe	0-255
7	Red	0-255
8	Green	0-255
9	Blue	0-255
10	White	0-255
11	Motor auto	16-255
12	Motor auto-Speed	0-255
13	Auto	8-255
14	Auto-Speed	0-255
15	Rest	250-255 (5SC)

21CH

Channel	Functions	DMX values
1	X	0-255
2	X-Pan	0-255
3	Y	0-255
4	Y-Tilt	0-255
5	Pan/Tilt Speed	0-255
6	Y-360	6-255
7	Dimming	0-255
8	Strobe	0-255
9	1 Red	0-255
10	1 Green	0-255
11	1 Blue	0-255
12	1 White	0-255
13	2 Red	0-255
14	2 Green	0-255
15	2 Blue	0-255
16	2 White	0-255
17	Motor auto	16-255
18	Motor auto-Speed	0-255
19	Auto	8-255
20	Auto-Speed	0-255
21	Rest	250-255 (5Sc)